



B9A Base

Current Equipment Type  
**TYPE ECF82**  
 MINIATURE  
 TRIODE PENTODE  
 FREQUENCY CHANGER



The BRIMAR ECF82 is a triode-pentode frequency changer featuring a high slope triode and a high input impedance pentode of high slope suitable for use in television receivers for Band III. The high input impedance at 200 Mc/s permits a sensibly constant conversion gain to be obtained over Bands I and III. The low value of  $C_{ag}$  for the pentode and  $C_{ap}$ , at facilitate the reduction of oscillator radiation. The use of low oscillator grid current to obtain the required heterodyne voltage reduces the frequency drift of the oscillator to a minimum.

Heater Current	... ..	0.45 amp.
Heater Voltage	... ..	6.3 volts (nom.)

**RATINGS**

Heater—Cathode Potential (cathode positive)	... ..	220 volts max.
Heater—Cathode Potential (cathode negative)	... ..	90 volts max.
Anode Voltage ( $I_a = 0$ )	... ..	550
Anode Voltage	... ..	300
Screen ( $g_2$ ) Voltage	... ..	—
Anode Dissipation	... ..	2.7
Screen Dissipation	... ..	—
Positive D.C. Grid No. 1 Voltage	... ..	0
Cathode Current	... ..	20
Grid Resistance	... ..	1

Triode

Pentode

**CHARACTERISTICS**

Anode Voltage	... ..	150	250 volts
Screen Voltage	... ..	—	110 volts
Cathode Bias Resistor	... ..	56	68 ohms
Anode Current	... ..	18	10 mA
Screen Current	... ..	—	3.5 mA
Mutual Conductance	... ..	8.5	5.2 mA/V
Anode Impedance (approx.)	... ..	5	400 k ohms
Amplification Factor	... ..	40	—
Grid No. 1 Voltage (for $I_a = 10 \mu A$ )	... ..	-12	-10 volts

Triode

Pentode

**TYPICAL OPERATION AS MIXER**

Anode Voltage	... ..	100	170	170 volts
Screen Voltage	... ..	—	110	170 volts
Cathode Bias Resistor	... ..	0	0	680 ohms
Grid Leak Resistor	... ..	27	270	100 k ohms
Anode Current	... ..	7.0	5.5	6.6 mA
Screen Current	... ..	—	2.0	2.5 mA
Heterodyne Voltage	... ..	—	3.0	5.0 volts peak
Conversion Conductance	... ..	—	1.6	1.65 mA/V

Triode

Pentode

**INTER-ELECTRODE CAPACITANCES \***

Pentode Grid No. 1 to Pentode Anode	... ..	0.006 pF
Pentode Input	... ..	5.0 pF
Pentode Output	... ..	3.5 pF
Triode Grid to Triode Anode	... ..	1.8 pF
Triode Grid to Cathode	... ..	2.5 pF
Triode Anode to Cathode	... ..	1.0 pF
Cathode to Heater (either section) approx.	... ..	3.0 pF

\* Measured with external shield.

Type ECF82 is a commercial equivalent of the CV5063.



